Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

Claim 1 (currently amended): A method for generating at least one sequence of random numbers of 1/f noise, which comprises the steps of:

determining a desired spectral value β;

determining a number of the random numbers of the 1/f noise to be generated;

determining an intensity constant const;

setting a starting value for a running variable n;

performing a loop-type repetition until a desired number of elements y(n) of a vector $\underline{y}$ of length n is calculated from 1/f-distributed random numbers, by the steps of:

increasing a current value of the running variable n by 1;

setting a simulation time step $[t_{n-1}; t_n]$;

Page 2 of 19

determining elements $\underline{C}_{ij}$ of a covariance matrix $\underline{\underline{C}}$ of

dimension (n × n) according to:

$$\underline{\underline{C}}_{ij} := const \cdot \left(-\left| t_j - t_i \right|^{\beta+1} + \left| t_{j-1} - t_i \right|^{\beta+1} + \left| t_j - t_{i-1} \right|^{\beta+1} - \left| t_{j-1} - t_{i-1} \right|^{\beta+1} \right)$$
$$i, j = 1, \ldots, n$$

determining an inverted covariance matrix $\underline{\underline{C}}^{-1}$ by inverting

the covariance matrix $\underline{\underline{C}}$;

determining a variable σ in accordance with

σ = sqrt(1 / e(n,n)),

where sqrt denotes a square root function, and e(n,n)

denotes an element of the inverted covariance matrix $\underline{\underline{C}}^{-1}$

indexed by (n,n);

determining a (0,1)-normally distributed random number

which forms an nth component of a vector $\underline{x}$ of length n;

forming a variable μ from first (n-1) components of an

nth row of the inverted covariance matrix $\underline{\underline{C}}^{-1}$ and (n-1)

elements of the vector $\underline{y}$ calculated for a preceding (n-1)

simulation time step, according to:

$$\mu := -\frac{y_{(n-1)}^T \cdot \underline{\underline{C}}^{-1}_{\bullet,n}}{\underline{\underline{C}}^{-1}_{n,n}}$$

where $y_{(n-1)}$ denotes first (n-1) elements of the vector $\underline{y}$,

$\underline{C}^{-1}_{\cdot,n}$ denotes the first (n-1) components of the nth row of

the inverted covariance matrix $\underline{C}^{-1}$, and $\underline{C}^{-1}_{n,n}$ denotes a

component of the inverted covariance matrix $\underline{C}^{-1}$ indexed by

(n,n); and

calculating an element y(n) of the vector $\underline{y}$ of length n

from the 1/f-distributed random numbers, according to:

$$y(n) = x(n) * \sigma + \mu\underline{;}$$

<u>outputting the at least one sequence of random numbers of 1/f</u>

<u>noise</u>.

Claim 2 (currently amended): A method for generating at least

one sequence of random numbers of 1/f noise, which comprises

the steps of:

determining a desired spectral value β;

determining a number of the random numbers of the 1/f noise to

be generated;

determining an intensity constant const;

Page 4 of 19

setting a starting value for a running variable n;

calculating q sequences of the random numbers of the 1/f noise simultaneously, by performing loop-type repetitions until a desired number of elements $y_{k,n}$ of a vector $\underline{y}$ of length n is calculated from 1/f-distributed random numbers, by the steps of:

increasing a current value of the running variable n by 1;

setting a simulation time step $[t_{n-1};\ t_n]$;

determining elements $\underline{C}_{ij}$ of a covariance matrix $\underline{C}$ of dimension (n × n) according to:

$$\underline{\underline{C}}_{ij} := const \cdot \left(-\left|t_j - t_i\right|^{\beta+1} + \left|t_{j-1} - t_i\right|^{\beta+1} + \left|t_j - t_{i-1}\right|^{\beta+1} - \left|t_{j-1} - t_{i-1}\right|^{\beta+1} \right)$$
$$i, j = 1, ..., n$$

determining an inverted covariance matrix $\underline{C}^{-1}$ by inverting the covariance matrix $\underline{C}$;

determining a variable σ in accordance with

$$\sigma = sqrt(1\ /\ e(n,n)\ ),$$

Page 5 of 19

where sqrt denotes a square root function, and e(n,n)

denotes an element of the inverted covariance matrix $\underline{\underline{C}}^{-1}$

indexed by (n,n);

determining a quantity q of (0,1)-normally distributed

random numbers $x_{k,n}$ which form a respective last component

of vectors $\underline{x}_k$ of length n, where k = 1, ..., q,

forming q variables μ_k according to:

$$\mu_k := -\frac{y_{(n-1),k}{}^T \cdot \underline{\underline{C}}^{-1}_{\bullet,n}}{\underline{\underline{C}}^{-1}_{n,n}}$$

where $y_{(n-1),k}$ denotes first (n-1) components of the vectors

$\underline{y}_k$ that were calculated for a preceding simulation time

step, $\underline{\underline{C}}^{-1}_{\bullet,n}$ denotes the first (n-1) components of the nth

row of the inverted covariance matrix $\underline{\underline{C}}^{-1}$, and $\underline{\underline{C}}^{-1}_{n,n}$ denotes

the element of the inverted covariance matrix $\underline{\underline{C}}^{-1}$ indexed

by (n,n), where k = 1, ..., q; and

calculating q elements $y_{k,n}$ which form a respective nth

component of the vector $\underline{y}_k$ of length n from 1/f-

distributed random numbers, according to:

$$y_{k,n} = x_{k,n} * \sigma + \mu_k,$$

where $k = 1, \ldots, q$;

<u>outputting at least one of the q sequences of random numbers</u>

<u>of 1/f noise.</u>

Claim 3 (original): A method for simulating a technical

system subject to 1/f noise, which comprises the steps of:

determining random numbers according to claim 1; and

using the random numbers for modeling variables present on

input channels of the technical system.

Claim 4 (original): A method for simulating a technical

system subject to 1/f noise, which comprises the steps of:

determining random numbers according to claim 2; and

using the random numbers for modeling variables present on

input channels of the technical system.

Claim 5 (original): A computer program, comprising:

computer-executable instructions for carrying out the method

according to claim 1 for determining the sequences of random

numbers of the 1/f noise.

Claim 6 (original): A computer program, comprising:

computer-executable instructions for carrying out the method

according to claim 2 for determining the sequences of random

numbers of the 1/f noise.

Claim 7 (original): A computer-readable data medium having

the computer-executable instructions according to claim 5.

Claim 8 (original): A computer-readable data medium having

the computer-executable instructions according to claim 6.

Claim 9 (original): A downloading method, which comprises the

step of:

downloading the computer program according to claim 5 from an

electronic data network onto a computer connected to the

electronic data network.

Claim 10 (original): The method according to claim 10, which further comprises using the Internet as the electronic data network.

Claim 11 (original): A downloading method, which comprises the step of:

downloading the computer program according to claim 6 from an electronic data network onto a computer connected to the electronic data network.

Claim 12 (original): The method according to claim 11, which further comprises using the Internet as the electronic data network.

Claim 13 (currently amended): A computer system, comprising:

~~means~~ processor programmed for executing the method for determining the sequences of random numbers of the 1/f noise according to claim 1.

Claim 14 (currently amended): A computer system, comprising:

Applic. No. 10/601,537
Response Dated September 11, 2006
Responsive to Office Action of June 9, 2006

~~means~~ processor programmed for executing the method for

determining the sequences of random numbers of the 1/f noise

according to claim 2.

Claim 15 (currently amended): A computer system, comprising:

~~means~~ processor programmed for executing the method for

determining the sequences of random numbers of the 1/f noise

according to claim 3.

Claim 16 (currently amended): A computer system, comprising:

~~means~~ processor programmed for executing the method for

determining the sequences of random numbers of the 1/f noise

according to claim 4.

Claim 17 (original): A method for simulating a technical

system subject to 1/f noise, which comprises the steps of:

determining random numbers according to claim 1; and

using the random numbers for fixing variables present on input

channels of the technical system.

Claim 18 (currently amended): A method for simulating a technical system subject to 1/f noise, which comprises the steps of:

determining random numbers according to claim [[1]]2; and

using the random numbers for fixing variables present on input channels of the technical system.